

8GB Computer memory DDR3 for Lenovo ThinkStation E32 UDIMM ECC





Your benefits ✓ verified quality memory ✓ 5 years warranty warranty details see last page ✓ 100% compatible ✓ free support on our hotline ✓ fast delivery

PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



Memory Specification



Memory size	8GB		
Memory technology	DDR3		
ECC support	ja		
JEDEC Norm	PC3-12800E		
DRAM Organization	512Mx8		
Rank	2Rx8		
Туре	UDIMM ECC (ECC unbuffered)		
Number of pins	240 Pin DIMM		
Memory data transfer rate	1600MHz @ CL11		
Speciality	-		
Board dimensions	133,35 x 30 (LxB mm)		
Operating temperature	0° C - 85° C		
Storage temperature	-40° C - +95° C		
RoHS compliant	Yes		
SKU	SP160305		
EAN	4055069317244		

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



System Specifications

The memory is 100% compatible with this sytem:

Device typeWorkstationDevice familyThinkStationDevice seriesE30 SerieDevice nameThinkStation E32Maximum memory*32GBNumber of memory sockets4	System manufacturer	Lenovo
Device series E30 Serie Device name ThinkStation E32 Maximum memory* 32GB	Device type	Workstation
Device name ThinkStation E32 Maximum memory* 32GB	Device family	ThinkStation
Maximum memory* 32GB	Device series	E30 Serie
,	Device name	ThinkStation E32
Number of memory sockets 4	Maximum memory*	32GB
	Number of memory sockets	4

^{*}The specifications for the maximum memory upgrade may differ from those of the manufacturer Lenovo. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Information on memory configuration

The following technical specifications should be considered in advance:

- Im Gerät können non ECC or ECC (Error-Correction-Code) RAM-memory installiert werden. Memory with der Description ECC besitzen eine Fehlerkorrektur.
- Non ECC memory modules cannot be used together with ECC memories.
- If a memory expansion is to be made with the already existing RAM memories, it must be checked which memory technology (non ECC / ECC) is already existing in the system.
- A higher memory clock of the memory module automatically adapts to the memory clock specified by the system. This can be the case especially with larger capacities.

Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.



Further memory options for Lenovo ThinkStation E32

Size	SKU	Technology	Туре	Number of pins	Brand	Reference no.
4GB	SP160306	DDR3	UDIMM (Non- ECC unbuffered)	240 Pin DIMM	PHS-memory®	0A65729
4GB	SP160304	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	0C19499, 03T7802, 03T7806, 0B47377
8GB	SP160307	DDR3	UDIMM (Non- ECC unbuffered)	240 Pin DIMM	PHS-memory®	0A65730
8GB	SP160305	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	03T7804, 0C19500, 03T7807, 0B47378

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.





Contact Information

PHS-electronic gmbh - www.phs-memory.com -Karl-Götz-Str. 5 97424 Schweinfurt Germany Phone: +49 9721 784678 E-Mail: info@phs-memory.com Web: www.phs-memory.com

All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.com