

8GB Computer memory DDR4 for Gigabyte R180-F2A RDIMM





5 years warranty Warranty details see last page

100% compatible

fast delivery

free support on our hotline

PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



Memory Specification



Memory size	8GB	
Memory technology	DDR4	
ECC support	yes	
JEDEC Norm	PC4-2133P-R	
Туре	RDIMM (ECC Registered)	
Number of pins	288 Pin DIMM	
Memory data transfer rate	2133MHz @ CL15	
Voltage	1,2 Volt	
Speciality	-	
Board dimensions	133,35 x 31,25 (LxB mm)	
Operating temperature	0° C - 85° C	
Storage temperature	-40° C - +95° C	
RoHS compliant	yes	
SKU	SP364653	
EAN	4064578277161	

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



System Specifications

The memory is 100% compatible with this sytem:

System manufacturer	Gigabyte
Device type	Server
Device family	Rack Server
Device series	R180 Serie
Device name	R180-F2A
Maximum memory*	6TB / 1,5TB according to manufacturer
Number of memory sockets	24

^{*} The specifications for the maximum memory upgrade may differ from those of the manufacturer Gigabyte. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Information on memory configuration

The following technical specifications should be considered in advance:

- The system supports RDIMM and RDIMM 3DS (Registered DIMM) or LRDIMM and LRDIMM 3DS (Load Reduced DIMM) memory modules. Large memory capacities can be realised with LRDIMM 3DS modules.
- RDIMM and RDIMM 3DS memory modules cannot be operated together with LRDIMM and LRDIMM 3DS main memories.
- If a memory expansion is to be made with the already existing RAM memories, it must be checked which basic memory technology (RDIMM / LRDIMM) is available.
- Memory slots without a processor may not be used.
- If memory modules are provided with higher speeds than specified by the system, the memory speed is automatically adjusted to the system specifications.

memory for Intel Xeon CPUs:

CPU / System	RDIMM	LRDIMM	
Xeon E5-16xx v3	8GB RDIMM	32GB LRDIMM	
Xeon E5-26xx v3	16GB RDIMM	64GB LRDIMM DDP	
Xeon E5-46xx v3	32GB RDIMM	128GB LRDIMM DDP	
	64GB RDIMM DDP	128GB LRDIMM 3DS	
	128GB RDIMM 3DS	256GB LRDIMM 3DS	
	256GB RDIMM 3DS		



Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.



Further memory options for Gigabyte R180-F2A

Size S	SKU	Technology	Туре	Number of pins	Brand	Reference no.
8GB S	SP364653	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
16GB S	SP364651	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
32GB S	SP364652	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
64GB S	SP364650	DDR4	LRDIMM (ECC LR DIMM)	288 Pin DIMM	PHS-memory®	
64GB S	SP469458	DDR4	RDIMM (ECC Registered) 3DS	288 Pin DIMM	PHS-memory®	
128GB S	SP469461	DDR4	RDIMM (ECC Registered) 3DS	288 Pin DIMM	PHS-memory®	
128GB S	SP469455	DDR4	LRDIMM (ECC LR DIMM) 3DS	288 Pin DIMM	PHS-memory®	
128GB 5	SP471805	DDR4	LRDIMM (ECC LR DIMM)	288 Pin DIMM	PHS-memory®	
256GB S	SP469464	DDR4	RDIMM (ECC Registered) 3DS	288 Pin DIMM	PHS-memory®	
256GB S	SP469456	DDR4	LRDIMM (ECC LR DIMM) 3DS	288 Pin DIMM	PHS-memory®	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.





Contact Information

PHS-electronic gmbh - www.phs-memory.com -Karl-Götz-Str. 5 97424 Schweinfurt Germany Phone: +49 9721 784678 E-Mail: info@phs-memory.com Web: www.phs-memory.com

Product Datasheet | SP364653 8GB Computer memory for R180-F2A



All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.com