

128GB Computer memory DDR4 for Gigabyte MR91-FS0 LRDIMM





- verified quality memory
- 5 years warranty
 Warranty details see last page
- ✓ 100% compatible
- free support on our hotline
- fast delivery

PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



Memory Specification



Memory size	128GB
Memory technology	DDR4
ECC support	yes
JEDEC Norm	PC4-25600-L
DRAM Organization	8Gx4
Rank	4Rx4 (4DRx4 DDP)
Туре	LRDIMM (ECC LR DIMM)
Number of pins	288 Pin DIMM
Memory data transfer rate	3200MHz @ CL22
Voltage	1,2 Volt
Speciality	DDP
Board dimensions	133,35 x 31,25 (LxB mm)
Operating temperature	0° C - 85° C
Character bases are bases	
Storage temperature	-40° C - +95° C
RoHS compliant	-40° C - +95° C yes
RoHS compliant	yes

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



System Specifications

The memory is 100% compatible with this sytem:

System manufacturer	Gigabyte
Device type	Motherboard-memory
Device family	Server-Motherboard
Device series	MR91 Serie
Device name	MR91-FS0
Maximum memory*	6TB / 3TB according to manufacturer
Number of memory sockets	24

^{*} The specifications for the maximum memory upgrade may differ from those of the manufacturer Gigabyte. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Information on memory configuration

The following technical specifications should be considered in advance:

- The system supports RDIMM and RDIMM 3DS (Registered DIMM) or LRDIMM and LRDIMM 3DS (Load Reduced DIMM) memory modules. Large memory capacities can be realised with LRDIMM 3DS modules.
- RDIMM and RDIMM 3DS memory modules cannot be operated together with LRDIMM and LRDIMM 3DS main memories.
- If a memory expansion is to be made with the already existing RAM memories, it must be checked which basic memory technology (RDIMM / LRDIMM) is available.
- When using a multiprocessor system, the memory slots should always be configured identically for each CPU.
- Memory slots without a processor may not be used.
- If memory modules are provided with higher speeds than specified by the system, the memory speed is automatically adjusted to the system specifications.
- The CPU supports 6 DIMMs per memory channel.

Maximum memory speed of possible CPUs

Xeon CPUs of the 2nd generation are offered in Bronze, Silver, Gold or Platinum. The different processor series also support different maximum memory speeds:

Xeon	CPU-series	max. Speed MHz	max. memory capacity je CPU
Bronze	3200	2133	1 TB
Silver	4200	2400	1 TB
Gold	5200	2666	1 TB, 2 TB, 4,5 TB
Gold	6200	2666	1 TB, 2 TB, 4,5 TB
Platinum	8200	2933	1 TB, 2 TB, 4,5 TB
Platinum	9200	2933	1,5 TB



Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.



Further memory options for Gigabyte MR91-FS0

8GBSP366795DDR4RDIMM (ECC Registered)288 Pin DIMMPHS-memory®16GBSP366792DDR4RDIMM (ECC Registered)288 Pin DIMMPHS-memory®32GBSP366793DDR4RDIMM (ECC 288 Pin DIMMPHS-memory®	
Registered) 32GB SP366793 DDR4 RDIMM (ECC 288 Pin DIMM PHS-memory®	
· ·	
Registered)	
64GB SP366794 DDR4 RDIMM (ECC 288 Pin DIMM PHS-memory® Registered)	
64GB SP366791 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-memory® LR DIMM)	
128GB SP472389 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-memory® LR DIMM) 3DS	
128GB SP366790 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-memory® LR DIMM)	
128GB SP469617 DDR4 RDIMM (ECC 288 Pin DIMM PHS-memory® Registered) 3DS	
256GB SP472390 DDR4 RDIMM (ECC 288 Pin DIMM PHS-memory® Registered) 3DS	
256GB SP469615 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-memory® LR DIMM) 3DS	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.





Contact Information

PHS-electronic gmbh - www.phs-memory.com -Karl-Götz-Str. 5 97424 Schweinfurt Germany Phone: +49 9721 784678 E-Mail: info@phs-memory.com Web: www.phs-memory.com

Product Datasheet | SP366790 128GB Computer memory for MR91-FS0



All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.com